



63 (& ,) , & \$ 7 , 2 1 6
& \$ 7 & \$ 5 ' ' 2 2 5

- ◆ ' L P H Q V L R I Q W x 11" H x 3 1/2" D
- ◆ 0 D W H U L D P o u s h i n g 1 2 ga. Painted steel.
- ◆ 3 R Z H U ; 0 6 5 W A C , 20 or 40 VA UL listed transformer (provided with unit).
- ◆ (P H U J H Q F \ % 1 2 W . W A H B G E L C E L L on constant charge (for control of line voltage variation and short term telephone support only, R S W L) R Q D O
- ◆ 7 H O H S K R Q S t a n d a r d H o i c e g r a d e R J 1 1 C Jack.
- ◆ 0 R X Q W S u r f a c e .
- ◆ 0 H P R U \ 7 . N o n - v o l a t i l e .
- ◆ 6 K L S S L Q J : A d d i t i o n a l 7 l b s .
- * (1 (5 \$ /
- ◆ 2 S H U D W L Q J (Q . Y . T e m p . : 0 2 0 ° C @ W 6 0 ° C (CATV temp.: 0 to 40°C) Relative humidity: 5% to 95% non-condensing.
- ◆ 5 H O D \ 2 X F u r n a c e c o n t a c t 2 4 V @ 3 A M P .
- ◆) & & 5 H # C P W 7 4 F 6 3 3 3 1 M T E .

\$ 3 3 / , & \$ 7 , 2 1 6

- ◆ Residential gated communities or commercial use.
- ◆ Apartment buildings, Condominiums, Townhouses.
- ◆ Retirement homes / Convalescent homes.
- ◆ Hospitals, Office buildings, and Banks.

2 5 ' (5 , 1 * , 1) 2 5 0 \$ 7 , 2 1

Model	CARD Capacity
CAT2C3K	3,000
CAT2C6K	6,000
CAT2C16K	16,200

([S D Q G V W R ' R R U E \ R S W L R Q D O S O X J + R G P R G X O H) * + & & \$ 5

& \$ 3 \$ & , 7 , (6

- ◆ 16,200 cards, see ordering information.
- ◆ 2 Entrances standard, expandable up to 16 entrances max with & \$ 7 ' 5 (requires RS485 conversion kit (& \$ 7 5 6 & 2 1 9 . , 7) .
- ◆ i 2 3 7 . ' 5 D S O X J P R G X O H [S D Q G V L R Q S 7 V H U L H V I U R P U H D G H U V W R U H D G H U
- ◆ Controls as many as 255 relays for elevator and auxiliary control when adding the CATRLY8 (relay expansion modules).
- ◆ 16 time zones, 16 access levels and 16 access groups.
- ◆ (8) CAT CARDS can be connected to one phone line using MUI's (one each) and all can be programmed remotely.
- ◆ 13,000 Event Log Buffer (before wrapping)
- ◆ 56K baud modem.
- ◆ Programming for the latest versions of Microsoft Windows supported versions including Win 8 and 10 using optional SELCOM PREMIUM software.
- ◆ Code / Phone / Card capacities can be upgraded remotely by the factory, through authorized dealers only.

(; 3 \$ 1 6 , 2 1 2 3 7 , 2 1 ' , \$ * 5 \$ 0



& \$ 5



! 9

! , < :

) * + & & \$ 5