

**The Select Gate Designer Model III incorporates the latest user-friendly Voice Message technology making the SG3DMR very easy to own and operate.**

**With Voice messages for visitor and messages for owner keypad operation and programming, the SG3DMR is more capable than ever before.**

**Have DSL? No problem. The SG3DMR is also transparent to existing or new homeowner DSL lines.**



### **SG3DMR STANDARD FEATURES**

- Backlit Blue Keypad for easy night viewing.
- Voice messages for visitor convenience.
- RF Receiver for entrance control built-in.
- 26 Bit Wiegand input, for card reader, RF receiver and Slave Keypad.
- Supports 100 cards or transmitters, for access without using the keypad - each programmable by time zone and function as well as making them valid by date or permanent.
- 100 PIN codes, each programmable by time zone and function as well as making them valid by date or permanent.
- Voice message for entrance activation.
- 9 Programmable time zones.
- "Do Not Disturb" (through time zones).
- Call Forwarding programmable by time zone.
- 10 additional telephone numbers can be programmed, and called using the keypad.
- Works on the existing phone line.
- Programmable by keypad, Touch-Tone™ phone or modem.

### **SG3DMR**

- Latch entrances (gates) open from the keypad or remotely with a phone: Timed 1-99 seconds, 1 hour or indefinitely.
- Close entrances (gates) from the keypad or remotely with a phone.

### **SG3DMR MODEM FEATURE**

- SG3DMR systems are shipped with a 2400 baud modem and software.
- Separate dial-up line not needed.

### **SG3DMR OPTIONS**

- Select Pass transmitters and/or HID cards - 100 total.
- Wiegand Input HID card reader.
- Long Range proximity cards and reader.
- Wiegand input Slave Keypad for exit or second entrance.
- 36", 42" or 48" Pedestals.
- Internal Camera, Color or Black and White with analog coax output. Transformer supplied.

## FEATURES

- Built-in RF 26 Bit Wiegand device input.
- Voice message assist in programming mode.
- Voice feedback on invalid key entries.
- Voice message when house line busy.
- Ability to work with a PBX system.
- 100 Cards or Transmitters, that can be used for visitors or deliveries and timed by start and end date (364 days out). Also programmable by time zone and function.
- 100 PIN Codes, that can be used for visitors / deliveries and timed by start and end date (364 days out). Also programmable by time zone and function.
- Local and remote latching (opening) of the entrances from 1- 99 seconds, 1 hour, or indefinitely.
- Programmable unlock time.
- Programmable talk time.
- Local call waiting and transfer.
- Large Event Log Buffer (approx. 800).
- LED long life lighting.
- 2 Form C relays standard.
- Postal lock inputs available (REX).
- Multi-level surge suppression.
- Weather resistant housing.
- Battery charging output.
- Open keypad programmable for voice mail.
- Select Gate Software Package provided with SG3DMR for remote programming and retrieving the event log buffer.

## OPTIONS

- **Wiegand Input** HID Card Reader.
- **Select Pass** Transmitters / Receivers.
- **Long Range Proximity** Cards and Reader.
- **Wiegand Input** Slave Keypad.
- **Pedestals** - 36", 42" or 48".
- **Special Metal Finishes.**
- **Camera**, internal Color or Black and White.
- **Network** interface option (NIC).
- **Serial Programming Module** (OPTSGSER)

## SPECIFICATIONS

- **Mounting dimensions:**  
SG3DMR 7" H x10" W x 6" D
- **Construction:**  
Back box: .090 aluminum, primed and painted black texture for exterior use.
- **Power Input:**  
16.5 VAC 20 VA plug-in transformer supplied or 12VDC @ 120 ma (nominal).
- **Telephone Interconnect:**  
RJ31X jack supplied.
- **Operating Environment:**  
Temperature -20 F to +140 F, Relative Humidity 5% to 95% non-condensing.
- **Relay Output (2):**  
Form C dry contact, 24 V @ 3 AMPS.
- **Mounting:** Surface or Pedestal.
- **Memory Type:** non-volatile.
- **Tone Detection:**  
Crystal controlled capable of detecting short burst 50 MS. DTMF tone, (detects touch-tones only).
- **Shipping Weight:** Approx. 9 lbs.

## APPLICATIONS

- **Residential** with or without a pedestrian gate.
- **Small** gated community with 10 homes or less. Card access used for residents.
- **Retirement homes** / Convalescent homes. Visitors use Push to Call to supervisors desk. Card access used for employees. Optional camera shows the visitor.
- **Hospitals:** Visitors use Push to Call to place call to Security. Card access used for Doctors.
- **Office buildings:** Push to Call used by visitors to call receptionist. Employees use card access for entrance. Optional camera shows visitor.
- **Small Factories or Companies:**  
(Push to Call used by visitors to call receptionist). Employees use card access for entrance. Optional camera shows visitor.